

3 PHASE

PUMP MOTOR H/P	VOLTS 3 PHASE	FULL LOAD AMPS	START AMPS	FUSE SLOW BLOW	SWITCH SIZE	CIRCUIT BREAKER SIZE	MIN. WIRE SIZE
20	208	70	166	90 A	100A	125FA	#3
	230	62	143	80 A	100A	110KA	#4
	460	31	71	40 A	60A	60FA	#8

2006

PUMP MOTOR H/P	VOLTS 3 PHASE	FULL LOAD AMPS	START AMPS	FUSE SLOW BLOW	SWITCH SIZE	CIRCUIT BREAKER SIZE	MIN. WIRE SIZE
25	208	82	186	100 A	100A	175FA	#1
	230	73	166	100 A	100A	150KA	#2
	460	36	83	40 A	60A	70FA	#6

PUMP MOTOR H/P	VOLTS 3 PHASE	FULL LOAD AMPS	START AMPS	FUSE SLOW BLOW	SWITCH SIZE	CIRCUIT BREAKER SIZE	MIN. WIRE SIZE
30	208	100	241	125 A	200A	200LA	#0
	230	86	195	125 A	200A	175KA	#1
	460	43	97	50 A	60A	80FA	#6

PUMP MOTOR H/P	VOLTS 3 PHASE	FULL LOAD AMPS	START AMPS	FUSE SLOW BLOW	SWITCH SIZE	CIRCUIT BREAKER SIZE	MIN. WIRE SIZE
40	208	121	299	150F	200A	250FA	#0
	230	106	241	150 A	200A	225KA	#0
	460	53	120	70 A	100A	110KA	#4